


16 AWG ARMCON



| Product Code | # of Cond. | Amp @ 30°C | Nominal OD inner jacket | | Nominal OD Armour | | Nominal OD Outer Jacket | | Weight Aluminum (Armoured) | |
|--------------|------------|------------|-------------------------|------|-------------------|------|-------------------------|------|----------------------------|---------|
| | | | mm | In | mm | In | mm | In | lbs/mft | kg/km |
| 46A1602-40 | 2 | 10 | 8.79 | 0.35 | 14.88 | 0.59 | 17.73 | 0.7 | 195 | 290.22 |
| 46A1603-40 | 3 | 10 | 9.49 | 0.37 | 15.6 | 0.61 | 18.43 | 0.73 | 216.12 | 321.62 |
| 46A1604-40 | 4 | 8 | 10.25 | 0.4 | 16.36 | 0.64 | 19.2 | 0.76 | 238.06 | 354.27 |
| 46A1605-40 | 5 | 8 | 10.92 | 0.43 | 17.02 | 0.67 | 19.87 | 0.78 | 259.84 | 386.68 |
| 46A1606-40 | 6 | 8 | 11.84 | 0.47 | 17.93 | 0.71 | 20.78 | 0.82 | 284.81 | 423.85 |
| 46A1607-40 | 7 | 7 | 12.75 | 0.5 | 18.85 | 0.74 | 21.69 | 0.85 | 310.22 | 461.66 |
| 46A1608-40 | 8 | 7 | 14.46 | 0.57 | 20.55 | 0.81 | 23.4 | 0.92 | 360.81 | 536.94 |
| 46A1610-40 | 10 | 7 | 15.65 | 0.62 | 21.74 | 0.86 | 24.59 | 0.97 | 397.91 | 592.15 |
| 46A1612-40 | 12 | 7 | 16.1 | 0.63 | 22.2 | 0.87 | 25.05 | 0.99 | 427.17 | 635.7 |
| 46A1615-40 | 15 | 7 | 17.32 | 0.68 | 23.42 | 0.92 | 26.26 | 1.03 | 478.14 | 711.55 |
| 46A1620-40 | 20 | 7 | 19.61 | 0.77 | 25.2 | 0.99 | 28.04 | 1.1 | 613.89 | 913.57 |
| 46A1625-40 | 25 | 6 | 22.76 | 0.9 | 28.85 | 1.14 | 31.7 | 1.25 | 759.63 | 1130.46 |
| 46A1630-40 | 30 | 6 | 24.01 | 0.95 | 30.1 | 1.19 | 32.9 | 1.3 | 834.31 | 1241.59 |
| 46A1640-40 | 40 | 6 | 26.72 | 1.05 | 32.82 | 1.29 | 35.66 | 1.4 | 1008.65 | 1501.04 |
| 42A1650-40 | 50 | 6 | 29.59 | 1.16 | 35.69 | 1.41 | 38.52 | 1.52 | 1174.61 | 1748 |

16 AWG ARMCON CONNECTORS

| No. of Cond. | Product Code | Connectors | | | |
|--------------|--------------|------------------|---------------|-----------------|-----------|
| | | OZG/Crouse Hinds | EGS/Iberville | Explosion Proof | Resin |
| 2 | 46A1602-40 | 41TECK0502 | 41TMC2050075A | 41TMC2X050075A | RAPIDEX30 |
| 3 | 46A1603-40 | 41TECK0503 | 41TMC2050099A | 41TMC2X050099A | RAPIDEX30 |
| 4 | 46A1604-40 | 41TECK0503 | 41TMC2050099A | 41TMC2X050099A | RAPIDEX30 |
| 5 | 46A1605-40 | 41TECK0503 | 41TMC2050099A | 41TMC2X050099A | RAPIDEX30 |
| 6 | 46A1606-40 | 41TECK0503 | 41TMC2050099A | 41TMC2X050099A | RAPIDEX30 |
| 7 | 46A1607-40 | 41TECK0755 | 41TMC2075118A | 41TMC2X075118A | RAPIDEX30 |
| 8 | 46A1608-40 | 41TECK0755 | 41TMC2075118A | 41TMC2X075118A | RAPIDEX30 |
| 10 | 46A1610-40 | 41TECK0755 | 41TMC2075118A | 41TMC2X075118A | RAPIDEX30 |
| 12 | 46A1612-40 | 41TECK0755 | 41TMC2075118A | 41TMC2X075118A | RAPIDEX30 |
| 15 | 46A1615-40 | 41TECK0756 | 41TMC2075118A | 41TMC2X075118A | RAPIDEX30 |
| 20 | 46A1620-40 | 41TECK1007 | 41TMC2100137A | 41TMC2X100137A | RAPIDEX30 |
| 25 | 46A1625-40 | 41TECK1007 | 41TMC2100137A | 41TMC2X100137A | RAPIDEX30 |
| 30 | 46A1630-40 | 41TECK1258 | 41TMC2125162A | 41TMC2X125162A | RAPIDEX30 |
| 40 | 46A1640-40 | 41TECK1258 | 41TMC2125162A | 41TMC2X125162A | RAPIDEX30 |
| 50 | 46A1650-40 | 41TECK1259 | 41TMC2125162A | 41TMC2X125162A | RAPIDEX30 |